


MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

QUOTATION CALL FOR

**SUPPLYING, INSTALLING, TESTING, AND COMMISSIONING OF 07 KWP CAPACITY
GROUND MOUNTED GRID CONNECTED SPV SYSTEM FOR WATER SUPPLY SCHEME OF
GRAMPANCHAYAT VAJEGAON TAL. KADEGAON DIST. SANGLI.**



DIVISIONAL OFFICE
MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR
MAHARASHTRA, KOLHAPUR

(A Government of Maharashtra Institution)

Address: C.S.NO.249/A-1/55, EWARD, MHADA COMPLEX, NAGALAPARK,
NEAR ZILLAPARISHAD, KOLHAPUR-416003 (M.S)

Contact No.0231-2680009,

Email:medakolhapur@mahaurja.com

Website (for Tender): <https://mahatenders.gov.in>

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

2023/DOK/Technical/Desk -1/Quotation/S-40/211

Date: 05/03/2024

Quotation Call

To,
(Contractor)

Sub: Supplying, Installing, Testing, and Commissioning of 07 KWp capacity Ground Mounted Grid Connected SPV System for Water Supply Scheme of Grampanchayat Vajegaon Tal. Kadegaon Dist. Sangli – Invitation to Quote

With reference to subject matter, we would like to invite your quote in sealed condition for undertaking the work with given technical specifications and technical standards with following terms and conditions –

- **Details and Dates: -**

Sr.No.	System details	Name of Site	Project Capacity
1	07 KWp capacity Ground Mounted Grid Connected SPV System for Water Supply Scheme of Grampanchayat Vajegaon Tal. Kadegaon Dist. Sangli	Water Supply Scheme of Grampanchayat Vajegaon Tal. Kadegaon Dist. Sangli	07 Kwp
2	Estimated Cost (Rs.)	4,75,001 /- (Inclusive of all taxes and charges)	
3	Date and time for submission of quotation.	From 06/03/2024; 10:00 Hrs to 12/03/2024 18:00 Hrs	
4	Date and time for opening of quotation.	13/03/2024; 10:00 Hrs	
5	Security Deposit	15,000/- (to be deposited online in favor of Maharashtra Energy Development Agency, Kolhapur)	
6	Address for communication and for quotation opening	Maharashtra Energy Development Agency, Divisional Office Kolhapur SR.No. 249/A-1/55, E Ward, MHADA complex, Nagala Park, Near Zilla Parishad, Kolhapur-416003	
7	Site location	Grampanchayat Vajegaon, Tal.Kadegaon, Dist. Sangli	

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

1. ELIGIBILITY CRITERIA –

The contractor shall be eligible to quote for this work provided fulfilment of following.

1. Shall have a registered firm/company with GST registration.
2. Shall provide brief information in prescribed format (enclosed).
3. Shall not be black listed in any govt. dept. and/or other organizations in and outside the state.
4. Shall provide documentary proof about having experience of supply, installation, testing and commissioning of minimum 10 KW of SPV Solar Power Plant.
5. Shall have an annual average turnover of Rs. 20 lakh per year for FY 2021-22 and 2022-23 duly certified by chartered accountant.
6. Shall provide self-attested copy of IT returns for FY 2021-22 and 2022-23 (Assessment year 2022-23 and 2023-24)
7. Shall have arrangement of providing after sales service within Kolhapur division.

2. TERMS AND CONDITIONS –

- 1) Location/Area for installation of Solar Power Plants shall be assigned immediately by the user agency to the selected contractor to get the work done in stipulated time.
- 2) The installation of Solar Power Plant should be done in excellent manner and meet technical standards prescribed by the MEDA.
- 3) As per the technical criteria set by the Ministry of New and Renewable Energy, Govt. of India the solar modules should fulfill the IEC standards and shall be procured from manufacturer providing module with RFID tag.
- 4) The contractor shall provide valid test certificate of inverter from manufacturer.
- 5) The contractor shall provide Solar Modules from the approved Manufacturers which are enlisted in the MNRE's ALMM list.
- 6) The solar module should be engraved with name of company supplying the same along with installation date etc.
- 7) If the Solar Power Plant does not function as per given standards then the loss incurred shall be borne by the supplier and paid Grampanchayat Vajegaon, Tal.Kadegaon, Dist. Sangli.
- 8) If contractor fails to complete the work then Security Deposit will be forfeited and contractor shall be blacklisted.
- 9) Contractor shall give training of system operation to a person duly nominated by user agency and same shall be informed to divisional office Kolhapur.

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

- 10) The contractor shall successfully complete the project within timeframe set out by the MEDA. For this purpose, contractor shall provide Activity Bar Chart within a week time after issue of Work Order.
- 11) The contractor shall provide the user manual, warranty card to the user agency and copy of same shall be provided to MEDA Kolhapur.**
- 12) The contractor shall visit the site and ensure scope of work before submission of quote against the enquiry. In this context, the contractor should submit the Site Visit Report in given prescribed format along with this quote.
- 13) The work being of limited nature and to seek prompt after sales service the contractor within Kolhapur division will be preferred while allotting the work against the invited quotes. Required proof in this matter need to be submitted by concerned contractor along with quote.
- 14) The Contractor shall provide the detailed information about Company/firm in attached format (Contractor's Information sheet)
- 15) The contractor shall submit their quotation in two different sealed envelopes i.e. First envelop shall contains documents as per the technical eligibility criteria and Second envelop shall contain Financial details (quoted rate).**
- 16) The contractor shall mention the subject on each sealed envelope i.e Technical Envelop and Financial Envelop.**
- 17) The financial envelop of technically qualified contractor shall only be opened.**

3. INSURANCE:

1. The contractor shall provide insurance coverage ex-factory until commissioning of project and acceptance for replacement or repair of any part of the consignment due to natural calamity, theft, fire and Vandalism.
2. It is the responsibility of successful contractor to drawn the insurance of SPV system in the name of MEDA from the date of commissioning up to 05 Years period covering the natural calamity, theft, fire and vandalism of project. The Successful contractor should pay the necessary insurance premium for the said project.
3. In case one year of insurance is submitted against the work order. Letter from the insurance company mentioning their inability to provide 05 years of insurance shall be submitted by the contractor to our office. Moreover, the successful contractor has to give undertaking to provide ensure that the successive insurance before the expiry of each insurance period.

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

4. Insurance has to be drawn in the name of MEDA Kolhapur on behalf of user agency (name of the user agency to be mentioned in insurance policy). Any complaint registered due to natural calamity, theft, fire and Vandalism by user agency shall be attended by the contractor for settling the claims from user agency.
5. *In case of any loss encountered by the project due to Natural calamity, theft, fire and Vandalism etc. the contractor shall be responsible for filing the insurance claim towards loss attained by the project with the respective insurance company and ensure to get compensation.*

4. GRID CONNECTIVITY:

1. The successful contractor shall process the net meter application during the installation of system & obtain grid connectivity from distribution licensee & ensure its timely commissioning. In this case the successful contractor shall have to pay the Applicable fees.
2. Increase in sanctioned load/contract demand and other related requirements shall be completed by user agency in co-ordination with the contractor. In this context the processing fees shall be borne by the contractor and deposit amount for load extension shall be paid by the user agency to MSEDCL along with relevant documents.
3. The successful contractor shall check the requirements of Grid Connectivity for the system and complete the grid related work according to MSEDCL/MERC guidelines.
4. The successful contractor has to review & confirm type & capacity of existing CT/PT & transformer for compatibility with type & capacity of proposed Solar Power Generation System. Also, successful contractor shall have to arrange and attend the inspection by representative of DISCOM. Further all amendments and resolutions regarding the net metering procedure as per MSEDCL/MERC guidelines are applicable and contractor shall follow the same and complete the work accordingly.
5. In order to have timely application of net meter the contractor shall examine the pending electricity bill of user agency, if any and inform them to pay the pending electricity bill immediately.

5. COMPREHENSIVE MAINTENANCE CONTRACT (CMC)

1. The complete and commissioned Solar PV Power Plant must be guaranteed against any manufacturing/ design/ installation defects for a minimum period of 5 years.

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

2. PV modules used in Solar PV Power Plant must be guaranteed for their output peak watt capacity, which should not be less than 90% at the end of 12 years and 80% at the end of 25 years.
3. During the CMC period, MEDA shall have all the rights to cross check the performance of the Solar PV Power Plant. MEDA may carry out the frequent inspections of the Solar PV Power Plant installed. If during such inspection, if any part is not found as per the specified technical parameters, MEDA will take the necessary action. The decision of MEDA in this regard will be final and binding on the contractor.
4. Successful contractor shall have to provide office address and name of technical person with contact who is operating in Kolhapur district/division for timely maintenance of SPV system.
5. During the CMC period, timely cleaning of SPV panels (once in fortnight) of system shall be binding on the user agency.
6. Whole responsibility about timely recharge of the SIM of RMS system shall be binding on user agency.
7. After site visit the contractor shall submit plant visit report to MEDA which duly certified by authorized person of the concern user agency.
8. If any problem occurs in working of SPV System or its estimated energy saving is not getting achieved then successful contractor shall attend the system and rectify the problem immediately.
- 9. User Agency shall be responsible to provide security for the project after commissioning and ensure timely cutting of grass at the project site.**
10. After the completion of the CMC period (after 05 Years) User Agency shall be completely responsible for the maintenance/repair etc. of the project.
11. In case if contractor fails to provide service during the CMC period, the Performance Bank Guarantee and Security Deposit shall be forfeited and contractor shall be blacklisted.

Note: Successful contractor shall submit undertaking of Comprehensive Maintenance Contract for 5 Years on Rs. 500 Stamp Paper (Notarized).

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

6. TERMS OF PAYMENT:

- A. 80% of the total cost will be released after successful installation and commissioning of the system duly certified by contractor, Officer of MEDA & authorized person of User Agency along with submission of Joint Inspection Report ,Photos, Tax Invoice, one week energy generation report ,Insurance policy documents (covering Natural calamity, theft, fire and Vandalism) effective from date of commissioning up to the CMC period i.e. for 5 Years, Warranty Cards, Manuals, List of Solar Modules numbers, Test Reports also an undertaking of CMC for 5 years from date of commissioning of project need to be submitted.
- B. 20% of the total cost shall be released on receipt of Two month successful performance report generated automatically through Remote Monitoring System (RMS) as well as manually which should be duly certified by the contractor, Officer of MEDA & authorized person of User Agency and submission of performance bank guarantee of 10 % of total project cost from any Nationalized/Scheduled Bank valid for period of 5 years from date of commissioning of project.

7. DEDUCTION:-

- i. The TDS at the source will be deducted as per the Govt. rule and regulations.
- ii. MEDA will issue necessary certificates of TDS deduction.
- iii. C' / 'D' form will not be issued by MEDA.

8. BILLS TO BE ON PRINTED FORM (TAX INVOICE) :

- The contractor shall submit the Tax Invoice in terms of the 70:30 ratio for basic amount i.e. 70% for goods and 30% for services, respectively by adding applicable GSD on renewable energy projects (i.e. 12% GST on Goods and 18% GST on Services).
- Also contractor shall submit the Tax Invoice for Net Metering work and other related work with 18% GST.
- The contractor shall submit the two separate Tax Invoices of 80% and 20% amount while releasing the 80% and 20% payment respectively.(Do not submit the Tax Invoice of 100% amount while releasing the first stage 80% payment)

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

9. SECURITY DEPOSIT –

- i. A sum of **15,000 /-** shall be deposited by the selected contractor as security deposit by online mode in favor of 'Maharashtra Energy Development Agency, Kolhapur on or before issuing of Work Order.
- ii. If the contractor fails to execute the work in given time or terminates the order prematurely then the security deposit shall be forfeited and contractor shall be blacklisted and no excuses will be entertained.
- iii. The security deposit shall be returned to the contractor without interest after successful commissioning (i.e. all work is completed as per terms and conditions of work order) of system and receipt of two month successful performance report duly signed by user agency, MEDA official and representative of the contractor.

10. PENALTY –

- A penalty of 1/2% of the total project cost shall be imposed on the contractor against a delay of one week in project completion subject to a maximum of up to 10% of the total project cost. In case the penalty exceeds 10% of the total project cost, the given order will be canceled & the security deposit will be forfeited and the contractor shall be blacklisted.

11. TIME FRAME:

- The successful contractor shall be required to commission the project within 60 Days from the date of issue of work order.

12. EXTENSION :

- If project is not commissioned within the given time frame due to any inevitable reasons then contractor shall seek the time extension for the project at least 07 Days in advance before expiry of project completion period (60 Days) by giving satisfactory reasons for same. **However if the time extension is not taken before the project completion period then the penalty clause of work order shall be effective till the request is applied for the extension with MEDA.**

13. STAMP DUTY :

- The successful contractor has to pay the applicable stamp duty as per Maharashtra Stamp Act clause 10. D. (1) to the Stamp Collector Kolhapur against this work contract and the receipt of same has to be produced along with the invoice to our office.

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

14. SITE VISIT :

The contractor shall visit the site & carryout the survey along with officials of user agency (as mentioned in scope of work) and upload the site visit report along with photographs (with Lat. And Long.) Indicating that the survey is carried by the contractor as per given format.

15. CHECK LIST OF DOCUMENTS TO BE FURNISHED WITH QUOTATION –

- PAN and GST Details.
- Copy of IT Returns.
- Declaration on company letter head.
- Contractors Information Sheet.
- Annual Turnover Certificate.
- Work Experience Details.
- Site Visit Report.(in format)

We look ahead to seek your sealed quotation on or before 12/03/2024 till 18 Hrs.

Thanking you,

Sd/-

Divisional General Manager
MEDA, Divisional Office, Kolhapur

Encl. :-

1. Contractor Information Sheet.
2. Declaration Format.
3. Annual Turn Over certificate format.
4. Site Survey Form.
5. Technical Specifications of Grid Connected System.

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

CONTRACTOR'S INFORMATION

Sr.No	Particulars	
1	Name of Firm	
2	Details of Mailing Address	
3	Firm Status (PSU/Incorporate/Ltd/Pvt.Ltd/LLP/Partnership/Proprietary)	
4	Name & Designation Of Contact Person	
5	Contact No.	
6	E-mail Address for correspondence	
7	Firm website Address	
8	Firm registration No/ROC Establish Year of firm	
9	PAN No.	
10	GST No.	
11	Turnover (in Rs.) for FY 2021-22 and 2022-23	
12	Skilled manpower	
13	*Experience in SPV Power Pack (On-Grid) in Kwp	
14	*Experience in SPV Power Pack (Off-Grid) in Kwp	

Authorised Sign and Stamp

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

DECLARATION

(On company's letter head)

To,

Divisional General Manager,

Divisional Office Kolhapur

Maharashtra Energy Development Agency

(A Government of Maharashtra Institution)

Address: C. S. No. 249/A – 1/55, E Ward, Mhada Complex, Nagala Park, Near Zilla Parishad,
Kolhapur - 416003

Respected Sir/Madam,

1. We have carefully read and understood all the terms and conditions of the quotation and hereby convey our acceptance to the same.
2. The information / documents furnished along with our offer are true and authentic to the best of my knowledge and belief, We are well aware of the fact that furnishing of any false information/ fabricated document would lead to rejection of our quotation at any stage besides liabilities towards prosecution under appropriate law.
3. We have apprised our self fully about the job to be done during the currency of the period of agreement and also acknowledge bearing consequences to of non-performance or deficiencies in the services on our part.
4. We have no objection, if enquiries are made about the work listed by us.
5. We have not been barred or blacklisted by any Government Agency / Department/ PSU or any such competent Government authority, organization where we have worked. Further, if any of the partners/directors of the organization /firm is blacklisted or having any criminal case against them, our quote shall not be considered. At any later point of time, if this information is found to be false, Divisional General Manager, Divisional Office Kolhapur, Maharashtra Energy Development Agency, may terminate the assigned contract immediately.
6. We have not been found guilty by a court of law in India for fraud, dishonesty or moral turpitude.
7. We agree that the decision of Divisional General Manager, MEDA, Divisional Office Kolhapur, in selection of quotation and shall final and binding to us.

For
(Company Name)

Name of signing authority / Designation / Place / Date

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

Annual Turnover

Each Contractor must fill in this form including private/public limited company.

- **Annual Turnover Data for the FY 2021-22,2022-23**
- **Name of Company :**

Year	Rs in Lacs
2021-22	
2022-23	

The information supplied should be the Annual Turnover of the Contractor in terms of the amounts billed to clients for each year for work in progress or completed.

Signature of Applicant

Certified by Applicant's Auditor

(Affix Stamp)

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

SITE VISIT REPORT

(To be submitted on letterhead of contractor)

Date: _____

To,
The Divisional General Manager,
Divisional Office Kolhapur,
Maharashtra Energy Development Agency
(A Government of Maharashtra Institution)
Address: C. S. No. 249/A – 1/55, E Ward, Mhada Complex, Nagala Park, Near Zilla
Parishad, Kolhapur – 416003.

Sub. : Site Visit Report for Supplying, Installing, Testing, and Commissioning of Ground Mounted 07 KWp capacity Grid Connected SPV System for Water Supply Scheme of Grampanchayat Vajegaon Tal. Kadegaon Dist. Sangli.

Ref.: Quotation Call No.Date:

Sir,

This has reference to above referred quotation call for Supplying, Installing, Testing, and Commissioning of Ground Mounted 07 KWp capacity Grid Connected SPV System for Water Supply Scheme (Consumer No :) of Grampanchayat Vajegaon Tal. Kadegaon Dist. Sangli in state of Maharashtra.

I / We hereby declare that we have visited the site.

I / We have made my ourselves acquainted with site conditions, approach to site, requirement of area, availability of water, requirement of grid connectivity from MSEDCL and requirement of all quotation conditions etc.

I / We have verified all details required to execute the project.

I / We have no problems in undertaking the project and complete them in the given time period.

Thanking you

Yours faithfully,
(Signature of Contractor)

Name of Contractor -----

Designation -----

Seal:

Signature of User Agency authorities.

Seal:.....

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

TECHNICAL SPECIFICATIONS

A. GRID CONNECTED SPV POWER PLANT

1. DEFINITION :-

A Grid Tied Solar Rooftop Photovoltaic (SPV) power plant consists of SPV array, Module Mounting Structure, Power Conditioning Unit (PCU) consisting of Maximum Power Point Tracker (MPPT), Inverter, and Controls & Protections, interconnect cables, Junction boxes, Distribution boxes and switches. PV Array is mounted on a suitable structure. Grid tied SPV system should be designed with necessary features to supplement the grid power during day time. Components and parts used in the SPV power plants including the PV modules, metallic structures, cables, junction box, switches, PCUs etc., should conform to the BIS or IEC or international specifications, wherever such specifications are available and applicable. Solar PV system shall consist of following equipment's/components.

Solar PV modules consisting of required number of Crystalline PV cells. Grid interactive Power Conditioning Unit with Mounting structures Junction Boxes. Earthing and lightning protections. IR/UV protected PVC Cables, pipes and accessories

2. SOLAR PHOTOVOLTAIC MODULES :-

- a) The PV modules used should be made in India.
- b) The PV modules used must qualify to the latest edition of IEC PV module qualification test or equivalent BIS standards Crystalline Silicon Solar Cell Modules IEC 61215/IS14286. In addition, the modules must conform to IEC 61730 Part-1 - requirements for construction & Part 2 – requirements for testing, for safety qualification or equivalent IS.
- c) For the PV modules to be used in a highly corrosive atmosphere throughout their lifetime, they must qualify to IEC 61701.
- d) The total solar PV array capacity should not be less than assigned **project capacity** and should comprise of solar crystalline modules of minimum 250 Wp and above wattage. Adequate protective devices against surges at the PV module shall be provided. Low voltage drop bypass diodes shall be provided.
- e) PV modules must be tested and approved by one of the IEC authorized test centres.
- f) The module frame shall be made of corrosion resistant materials, preferably having anodized aluminum.
- g) Other general requirement for the PV modules and subsystems shall be the Following:
 - The rated output power of any supplied module shall have tolerance within +/-3%.
 - The peak-power point voltage and the peak-power point current of any supplied module and/or any module string (series connected modules) shall not vary by more than 2 (two) per cent from the respective arithmetic means for all modules and/or for all module strings, as the case may be.
 - The module shall be provided with a junction box with either provision of external screw terminal connection or sealed type and with arrangement for provision of by-pass diode. The box shall have hinged, weather proof lid with captive screws and cable gland entry points or may be of sealed type and IP-65 rated.

3. SOLAR PV MODULES :-

- h) Modules deployed must use a RF identification tag. The following information must be mentioned in the RFID used on each modules. This should be inside the laminate only.

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

- a. Name of the manufacture of the PV module
- b. Name of the manufacture of Solar Cells.
- c. Month & year of the manufacture (separate for solar cells and modules)
- d. Country of origin (separately for solar cells and module)
- e. I-V curve for the module Wattage, I_m , V_m and FF for the module
- f. Unique Serial No and Model No of the module
- g. Date and year of obtaining IEC PV module qualification certificate.
- h. Name of the test lab issuing IEC certificate.
- i. Other relevant information on traceability of solar cells and module as per ISO 6001 and ISO 14001

4. **WARRANTIES :-**

- Material Warranty:
 - i. Material Warranty is defined as: The project developer should warrant the Solar Module(s) to be free from the defects and/or failures specified below for a period not less than five (05) years from the date of sale to the original customer ("Customer")
 - ii. Defects and/or failures due to manufacturing
 - iii. Defects and/or failures due to quality of materials
 - iv. Non conformity to specifications due to faulty manufacturing and/or inspection processes. If the solar Module(s) fails to conform to this warranty, the project developer will repair or replace the solar module(s), at the Owners sole option.
- Performance Warranty:
 - a. The predicted electrical degradation of power generated not exceeding 20% of the minimum rated power over the 25 year period and not more than 10% after ten years period of the full rated original output.

5. **ARRAY STRUCTURE (lower side 06 ft elevated) :-**

- i. Hot dip galvanized MS mounting structures having 80 micron thickness may be used for mounting the modules / panels / arrays.
- ii. Each structure should have angle of inclination as per the site conditions to take maximum insolation. However to accommodate more capacity the angle inclination may be reduced until the plant meets the specified performance ratio requirements.
- iii. The Mounting structure shall be so designed to withstand the speed for the wind zone of the location where a PV system is proposed to be installed (wind speed of 150 km/ hour). Suitable fastening arrangement such as grouting and calming should be provided to secure the installation against the specific wind speed.
- iv. The mounting structure steel shall be as per latest IS 2062: 1992 and galvanization of the mounting structure shall be in compliance of latest IS 4759.
- v. Structural material shall be corrosion resistant and electrolytically compatible with the materials used in the module frame, its fasteners, nuts and bolts.
- vi. **Aluminium structures also can be used which can withstand the wind speed of respective wind zone.** Necessary protection towards rusting need to be provided either by coating or anodization.
- vii. The fasteners used should be made up of stainless steel. The structures shall be designed to allow easy replacement of any module. The array structure shall be so designed that it will occupy minimum space without sacrificing the output from the SPV panels.
- viii. Regarding civil structures the Manufacturer/Supplier need to take care of the load bearing capacity of the roof and need arrange suitable structures based on the quality of roof.
- ix. The total load of the structure (when installed with PV modules) on the terrace should be less than 60 kg/m².

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

- x. The minimum clearance of the structure from the roof level should be 300 mm.

6. FOUNDATION FOR STRUCTURE :

Providing and laying in situ/Ready Mix cement concrete M-20 of trap/granite/quartzite/ gneiss metal for R.C.C. foundation of size 0.5x0.5x1 Mtr.

7. JUNCTION BOXES (JBs) :-

- i. The junction boxes are to be provided in the PV array for termination of connecting cables. The J. Boxes (JBs) shall be made of GRP / FRP / Powder Coated Aluminium /cast aluminium alloy with full dust, water & vermin proof arrangement. All wires / cables must be terminated through cable lugs. The JB's shall be such that input & output termination can be made through suitable cable glands.
- ii. Copper bus bars / terminal blocks housed in the junction box with suitable termination threads conforming to IP65 standard and IEC 62208 Hinged door with EPDM rubber gasket to prevent water entry. Single / double compression cable glands. Provision of earthing's. It should be placed at 5 feet height or above for ease of accessibility.
- iii. Each Junction Box shall have High quality Suitable capacity Metal Oxide Varistors (MOVs) / SPDs, suitable Reverse Blocking Diodes. The Junction Boxes shall have suitable arrangement monitoring and disconnection for each of the groups.
- iv. Suitable markings shall be provided on the bus bar for easy identification and the cable ferrules must be fitted at the cable termination points for identification.
- v. All fuses shall have DIN rail mountable fuse holders and shall be housed in thermoplastic IP 65 enclosures with transparent covers.

8. DC DISTRIBUTION BOARD :-

- DC Distribution board to receive the DC output from the array field.
- DC DBs shall have sheet from enclosure of dust & vermin proof conform to IP 65 protection. The bus bars are made of copper of desired size. Suitable capacity MCBs/MCCB shall be provided for controlling the DC power output to the PCU along with necessary surge arrestors.

9. AC DISTRIBUTION PANEL BOARD :-

- i) AC Distribution Board (DB) shall control the AC power from PCU/ inverter, and should have necessary surge arrestors. Interconnection from ACDB to mains at LT Bus bar while in grid tied mode.
- j) All switches and the circuit breakers, connectors should conform to IEC 60947, part I, II and III/ IS 60947 part I, II and III.
- k) The changeover switches, cabling work should be undertaken by the Manufacturer/Supplier as part of the project.
- l) All the Panel's shall be metal clad, totally enclosed, rigid, floor mounted, air - insulated, cubical type suitable for operation on three phase / single phase, 415 or 230 volts, 50 Hz
- m) The panels shall be designed for minimum expected ambient temperature of 45 degree Celsius, 80 percent humidity and dusty weather.
- n) All indoor panels will have protection of IP54 or better. All outdoor panels will have protection of IP65 or better.
- o) Should conform to Indian Electricity Act and rules (till last amendment).
- p) All the 415 AC or 230 volts devices / equipment like bus support insulators, circuit breakers, SPDs, VTs etc., mounted inside the switchgear shall be suitable for continuous operation and satisfactory performance under the following supply conditions

10. PCU / ARRAY SIZE RATIO :-

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

- The combined wattage of all inverters for each SPV power plant should not be less than the assigned project capacity at given location.
- Maximum power point tracker shall be integrated in the PCU/inverter to maximize energy drawn from the array.

11. PCU / INVERTER :-

- q) As SPV array produce direct current electricity, it is necessary to convert this direct current into alternating current and adjust the voltage levels to match the grid voltage. Conversion shall be achieved using an electronic Inverter and the associated control and protection devices. All these components of the system are termed the “Power Conditioning Unit (PCU)”. In addition, the PCU shall also house MPPT (Maximum Power Point Tracker), an interface between Solar PV array & the Inverter, to the power conditioning unit/inverter should also be DG set interactive. If necessary. Inverter output should be compatible with the grid frequency. Typical technical features of the inverter shall be as follows:

Switching devices	IGBT/MOSFET
Control	Microprocessor /DSP
Nominal AC output voltage and frequency	230 V /415V, 1/3 Phase, 50 Hz (In case single phase inverters are offered, suitable arrangement for balancing the phases must be made.)
Output frequency	50 Hz
Grid Frequency Synchronization range	+ 3 Hz or more
Ambient temperature considered	-20° C to 50° C
Humidity	95 % Non-condensing
Protection of Enclosure	IP-20(Minimum) for indoor.
	IP-65(Minimum) for outdoor.
Grid Frequency Tolerance range	+ 3 or more
Grid Voltage tolerance	-0.20.15
No-load losses	Less than 1% of rated power
Inverter efficiency(minimum)	>93% (In case of 10 kW or above with in- built galvanic isolation) >97% (In case of 10 KW or above without in-built galvanic isolation)
Inverter efficiency (minimum)	> 60% (In case of less than 10 kW)

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

THD	< 3%
PF	> 0.9

- a. PCU / inverter shall be capable of complete automatic operation including wake-up, synchronization & shutdown.
- b. The output of power factor of PCU inverter is suitable for all voltage ranges or sink of reactive power, inverter should have internal protection arrangement against any sustainable fault in feeder line and against the lightning on feeder.
- c. Built-in meter and data logger to monitor plant performance through external computer shall be provided.
- d. **Anti-islanding** (Protection against Islanding of grid): The PCU shall have anti islanding protection in conformity to IEEE 1547/UL 1741/ IEC 62116 or equivalent BIS standard.
- e. The PCU/ inverter generated harmonics, flicker, DC injection limits, Voltage Range, Frequency Range and Anti-Islanding measures at the point of connection to the utility services should follow the latest CEA (Technical Standards for Connectivity Distribution Generation Resources) Guidelines.
- f. The power conditioning units / inverters should comply with applicable IEC/ equivalent BIS standard for efficiency measurements and environmental tests as per standard codes IEC 61683/IS 61683 and IEC 60068-2 (1,2,14,30)/ Equivalent BIS Std.
- g. The MPPT units environmental testing should qualify IEC 60068-2 (1, 2, 14, 30)/ Equivalent BIS std. The junction boxes/ enclosures should be IP 65 (for outdoor)/ IP 54 (indoor) and as per IEC 529 specifications.
- h. The PCU / inverters should be tested from the MNRE approved test centres / NABL / BIS / IEC accredited testing- calibration laboratories. In case of imported power conditioning units, these should be approved by international test houses.

12. INTEGRATION OF PV POWER WITH GRID :-

The output power from SPV would be fed to the inverters which converts DC produced by SPV array to AC and feeds it into the main electricity grid after synchronization. In case of grid failure, or low or high voltage, solar PV system shall be out of synchronization and shall be disconnected from the grid. In case existing DG set comes into service, PV system shall again be synchronized with DG supply and load requirement would be met to the extent of availability of power. 4 pole isolation of inverter output with respect to the grid/ DG power connection need to be provided.

13. REMOTE MONITORING SYSTEM (RMS):

The contractor shall include the RMS equipment in the system that is capable to store & provide online performance data/parameters comprising AC voltage, AC current, output power, DC voltage, DC current, Time-On, Time-off, Power produced etc. The consolidated monthly RMS report shall automatically get generated in the system & provided by mail to MEDA & user agency.

The RMS portal address, along with user id and password shall be provided by supplier to MEDA and user agency after commissioning of the system.

14. POWER CONSUMPTION:

- Regarding the generated power consumption, priority need to give for internal consumption first and thereafter any excess power can be exported to grid.

15. PROTECTIONS :-

- The system should be provided with all necessary protections like earthing, Lightning, and grid islanding as follows:

16. LIGHTNING PROTECTION :-

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

- The SPV power plants shall be provided with lightning & overvoltage protection. The main aim in this protection shall be to reduce the over voltage to a tolerable value before it reaches the PV or other sub system components. The source of over voltage can be lightning, atmosphere disturbances etc. The entire space occupying the SPV array shall be suitably protected against Lightning by deploying required number of Lightning Arrestors. Lightning protection should be provided as per IEC 62305 standard. The protection against induced high-voltages shall be provided by the use of metal oxide varistors (MOVs) and suitable earthing such that induced transients find an alternate route to earth.

17. SURGE PROTECTION :-

- Internal surge protection shall consist of three MOV type surge-arrestors connected from +ve and -ve terminals to earth (via Y arrangement).

18. EARTHING PROTECTION :-

- Each array structure of the PV yard should be grounded/ earthed properly as per IS:3043-1987. In addition the lightning arrester/masts should also be earthed inside the array field. Earth Resistance shall be tested in presence of the representative of Department/MEDA as and when required after earthing by calibrated earth tester. PCU, ACDB and DCDB should also be earthed properly.
- Earth resistance shall not be more than 5 ohms. It shall be ensured that all the earthing points are bonded together to make them at the same potential.

19. GRID ISLANDING :-

- In the event of a power failure on the electric grid, it is required that any independent power-producing inverters attached to the grid turn off in a short period of time. This prevents the DC-to-AC inverters from continuing to feed power into small sections of the grid, known as "Islands." Powered Islands present a risk to workers who may expect the area to be unpowered, and they may also damage grid-tied equipment. The Rooftop PV system shall be equipped with islanding protection. In addition to disconnection from the grid (due to islanding protection) disconnection due to under and over voltage conditions shall also be provided.
- A manual disconnect 4-pole isolation switch beside automatic disconnection to grid would have to be provided at utility end to isolate the grid connection by the utility personnel to carry out any maintenance. This switch shall be locked by the utility personnel.

20. CABLES :-

- r) Cables of appropriate size to be used in the system shall have the following characteristics:
 - a. Shall meet IEC 60227/IS 694, IEC 60502/IS1554 standards
 - b. Temp. Range: -10°C to +80°C.
 - c. Voltage rating 660/1000V
 - d. Excellent resistance to heat, cold, water, oil, abrasion, UV radiation
 - e. Flexible
 - f. Sizes of cables between array interconnections, array to junction boxes, junction boxes to Inverter etc. shall be so selected to keep the voltage drop (power loss) of the entire solar system to the minimum (2%)
 - g. For the DC cabling, XLPE or, XLPO insulated and sheathed, UV- stabilized single core multi-stranded flexible copper cables shall be used; Multi-core cables shall not be used.
 - h. For the AC cabling, PVC or, XLPE insulated and PVC sheathed single or, multi-core multi-stranded flexible copper cables shall be used; Outdoor AC cables shall have a UV-stabilized outer sheath.
 - i. The cables (as per IS) should be insulated with a special grade PVC compound formulated for outdoor use. Outer sheath of cables shall be electron beam cross-linked XLPO type and black in colour.
 - j. The DC cables from the SPV module array shall run through a UV- stabilized PVC conduit

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

pipe of adequate diameter with a minimum wall thickness of 1.5mm.

- k. Cables and wires used for the interconnection of solar PV modules shall be provided with solar PV connectors (MC4) and couplers.
- l. All cables and conduit pipes shall be clamped to the rooftop, walls and ceilings with thermo-plastic clamps at intervals not exceeding 50 cm; the minimum DC cable size shall be 4.0 mm² copper; the minimum AC cable size shall be 4.0 mm² copper. In three phase systems, the size of the neutral wire size shall be equal to the size of the phase wires.
- m. Cable Routing / Marking: All cable/wires are to be routed in a GI cable tray and suitably tagged and marked with proper manner by good quality ferule or by other means so that the cable easily identified. In addition, cable drum no. / Batch no. to be embossed/ printed at every one meter.
- n. Cable Jacket should also be electron beam cross-linked XLPO, flame retardant, UV resistant and black in colour.
- o. All cables and connectors for use for installation of solar field must be of solar grade which can withstand harsh environment conditions including High temperatures, UV radiation, rain, humidity, dirt, salt, burial and attack by moss and microbes for 25 years and voltages as per latest IEC standards. DC cables used from solar modules to array junction box shall be solar grade copper (Cu) with XLPO insulation and rated for 1.1kV as per relevant standards only.
- p. The ratings given are approximate. Manufacturer/Supplier to indicate size and length as per system design requirement. All the cables required for the plant shall be provided by the Manufacturer/Supplier. Any change in cabling sizes if desired by the Manufacturer/Supplier shall be approved after citing appropriate reasons. (All cable schedules/ layout drawings shall be approved prior to installation.)
- q. Multi Strand, Annealed high conductivity copper conductor PVC type 'A' pressure extruded insulation or XLPE insulation. Overall PVC/XLPE insulation for UV protection Armoured cable for underground laying. All cable trays including covers to be provided. All cables conform to latest edition of IEC/ equivalent BIS Standards as specified below: BoS item / component Standard Description Standard Number Cables General Test and Measuring Methods, PVC/XLPE insulated cables for working Voltage up to and including 1100 V, UV resistant for outdoor installation IS /IEC 69947.
- r. The total voltage drop on the cable segments from the solar PV modules to the solar grid inverter shall not exceed 2.0%.
- s. The total voltage drop on the cable segments from the solar grid inverter to the building distribution board shall not exceed 2.0% FRLS Cables should be used.
- t. **AC Armored cable:** Supplying, erecting & terminating FR XLPE insulated, galvanised steel formed wire armoured (strip) cable 1100 V, 4 core 10 sq. mm. copper conductor complete erected with glands & lugs, on wall/ trusses/ pole or laid in provided trench/ pipe.
- u. **Protection for Armored cable :** Supplying and laying (including excavation of suitable width & depth up to 90 cm) 50 mm outside dia. double all corrugated pipes (DWC) of HDPE for enclosing cable below ground/road surface, to required depth.
- v. **Cable Tray for cables :** Providing & erecting Hot dipped galvanized ladder type cable tray manufactured from 16 swg (1.6 mm thick) GI sheet of 200 mm width & 100 mm height comprising all required standard accessories.

21. **DANGER BOARDS AND SIGNAGES:-**

- Danger boards should be provided as and where necessary as per IE Act. /IE rules as amended up to date.

22. **SAFETY MEASURES:-**

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

The Manufacturer/Supplier holder shall take entire responsibility for electrical safety of the installation(s) including connectivity with the grid and follow all the safety rules & regulations applicable as per Electricity Act, 2003 and CEA guidelines etc.

23. FIRE EXTINGUISHER (01 Nos) :

- Supplying & erecting Carbon Dioxide (CO₂) fire extinguisher of 4.5 kg. capacity cartridge type conform to IS 2878/15683 complete erected with necessary clamp made from 50 x 6 mm. M. S. flat with nut & bolts grouted in wall complete.

24. DISPLAY BOARD :-

- Providing and fixing board displaying information, such as 'Name of work, Tender cost, Name of Contractor, Work completion and liability period etc', having rectangular shape of 1.20mx0.90m size made out 18gauge(1.25mm) thick mild steel sheet painted with one coat of Zinc chromate stoving primer and two coats of enamel paint on front side and grey stove enamel on back side and border/messages/symbols etc. with approved colour shade paint complete, on M.S. angle of size 35x35x3mm frame with properly cross braced M.S. angles of size 35mmx35mmx3mm duly painted including Two M.S. angle iron posts of size 65mmx65 mmx 6mm, 3.65m long painted with alternate black and white bands of 25 cm width including all fixtures etc. and fixing the boards in 1:4:8 concrete block of size 60 cm x 60 cm x 75cm including, excavation, refilling, transportation, and labor etc complete.

-----X-----X-----X-----

B. NET METERING AND ADDITIONAL ELECTRICAL WORK

Sr. No.	Item	Rate	Per	Quantity	Amount
		Rs.			Rs.
1	2	3	4	5	6

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

1	Supplying and erecting three phase 10 to 60 A net meter DLMS compliance of accuracy class 1.0, 3 x 240V, 50 Hz, with backlit LCD display, optical port and RS232 port (measures import kWh, kVAh, export kWh, kVAh, Net kWh,kVAh,V, I, kW, 6 months history of energy) with wiring connections and mounting hardware on provided panels complete with calibration certificate from manufacturer (As per PWD CSR Elect. Item No. 6-5-13)	12298	Unit	1	12298
2	Supplying and erecting three phase smart energy meter DLMS compliance with 3x240V 50 cycles AC supply 10-60 A, accuracy class 1.0 with backlit LCD display, measuring & display V, I, kW, kWh, PF, kVA, kVAh, MD, day, week, month & with communication module configurable for GSM/Wi-Fi, IrDA/Bluetooth, complete provided panel with calibration certificate from manufacturer & duly wired with required size of PVC wires (As per PWD CSR Elect. Item No. 6-5-17)	21922	Unit	1	21922
3	Supplying, erecting & terminating FR XLPE insulated, galvanised steel wire armoured (round) cable, 1100 V 3 core 10 sq. mm. aluminium conductor complete erected with glands & lugs on wall/trusses/pole or laid in provided trench/ pipe as per specification no. CB-LT/AL (As per PWD CSR Elect. Item No. 7-1-10)	164	Mtr	15	2460
4	Net Meter testing Charges as per the rates mentioned in the MSDCL Circular No. CE(Dist)/M-III/ Schedule of Charges/09078 Date : 07/04/2020	1100	Unit	1	1100
5	Generation Meter Testing Charges as per the rates mentioned in the MSDCL Circular No. CE(Dist)/M-III/ Schedule of Charges/09078 Date : 07/04/2020	1100	Unit	1	1100
6	Installation Testing fees of renewable energy Project as per the rates mentioned in the MSDCL Circular No. CE(Dist)/M-III/ Schedule of Charges/09078 Date : 07/04/2020	1000	Unit	1	1000
7	Supplying and erecting GI strip of high purity required size used for earthing on wall and/or any other purpose with necessary GI clamps fixed on wall painted with bituminous paint with joints required. As per specification no EA-EP. (As per PWD CSR Elect. Item No. 9-2-3)	236	KG	3	708
8	Providing pipe type earthing with 40mm. dia. G.I. pipe or 20 mm dia. G.I. Rod complete with all materials testing and recording the results as per specification no.EA-EP (As per PWD CSR Elect. Item No. 9-1-4)	1537	unit	1	1537
9	Supplying and laying (including excavation of suitable width & depth up to 90 cm) 50 mm outside dia. double all corrugated pipes (DWC) of HDPE for enclosing cable below ground/road surface, to required depth complete. (as per PWD CSR Elect. 2023-24 Item No. 7-6-9)	204	Mtr	10	2040
10	Supplying, erecting & commissioning 4 pole RCCB 63A, electromagnetic type with 30/100/300 mA sensitivity with earth leakage trip indication complete as per specification no. SW-RCCB.(As per PWD CSR Elect. Item No. 5-6-6)	3092	unit	1	3092
11	Providing and fixing board displaying information, suchas 'Name of work, Tender cost, Name of Contractor, Work completion and liability period etc', having rectangular shape of 1.20mx0.90m size made out 18gauge(1.25mm) thick mild steel sheet painted with one coat of Zinc chromate stoving primer and two coats of enamel paint on front side and grey stove enamel on back side and border/messages/symbols etc. with approved colour shade	9920	unit	1	9920

MAHARASHTRA ENERGY DEVELOPMENT AGENCY, KOLHAPUR

	<p>paint complete, on M.S. angle of size 35x35x3mm frame with properly cross braced M.S. angles of size 35mmx35mmx3mm duly painted including Two M.S. angle iron posts of size 65mmx65mmx6mm, 3.65m long painted with alternate black and white bands of 25 cm width including all fixtures etc. and fixing the boards in 1:4:8 concrete block of size 60 cm x 60 cm x 75cm including, excavation, refilling, transportation, and labor etc complete. Spec. Number As directed by Engineer in Charge (as per PWD SSR Civil. Item No.6.36)</p>				
12	<p>Supplying & erecting Carbon Dioxide (CO2) fire extinguisher of 4.5 kg. capacity cartridge type conform to IS 2878/15683 complete erected with necessary clamp made from 50x6 mm. M. S. flat with nut & bolts grouted in wall complete. (as per PWD CSR Elect. Item No. 13-14-1)</p>	9943	unit	1	9943
	Total (A)				67120
	add 5% on Part B as per CSR guidelines (B)				70476
	18% GST on part 'E' (C)				12,686
	Total (B+C)				83162